

Driver – FridayForge Button Tile (10 Buttons) UI Tile Virtual

version 2.0.0

Driver

This release note is for the Crestron driver FridayForgeButtonTile.

This driver is the FridayForge Button Tile, a tile page with up to 10 buttons you name yourself. Pressing a button raises a Crestron Home event, so each button can trigger any scene, relay or device in Actions & Events.

Notes and Recommendations

A button with a blank label is hidden, so the page only shows the buttons you set up. Each button also has an action that presses it from a scene or schedule.

The driver works free for 2 hours after the processor starts. To keep using it, install the FridayForge License Manager and buy a licence for this driver at forgedbyfriday.com. A licensed driver keeps working only while the License Manager is installed and running on the same processor.

System Requirements and Dependencies

- Crestron Home OS 4.x with extension-device (UI tile) support

Installation/Upgrade Instructions

Installation

- Copy the .pkg file to the Crestron Home Configurator and install it (Settings > Drivers).
- Add the device in the Configurator and fill in the installer settings below. The tile needs no network address.
- Assign the tile to its room. In Actions & Events, use the tile's events as triggers and its actions as outputs.
- **After you install a newer version of the driver, you do not need to remove it.** If the update adds new settings, Crestron Home asks the installer to review them before the driver comes back online.

Installer Settings

Setting	Description
Show on Room Page	Show the tile on its room's page. Default: on.
Show on Home Page	Also show the tile on the Home page. Default: off.
Page Title	Title shown at the top of the button page. Required.
Tile Icon	Icon on the room/home tile. Default: icGenericDevice.
Button 1-10 Label	Label for the button. Leave blank to hide the button.
Button 1-10 Icon	Icon for the button. Default: icHome.
Debug Log	Troubleshooting only. Adds more detail to the driver log used in FridayForge support reports. Default: off.

CH Icon Reference	A link to Crestron's list of valid icon names, for the icon settings.
--------------------------	---

Using Driver Events in Sequences

Event	Raised when
Button 1 Pressed ... Button 10 Pressed	The button is pressed on the tile page or by the matching action.

Actions: **Press Button 1** through **Press Button 10**.

End-User Experience

What Appears in Crestron Home

Item	Description
Button tile	One tile with a page of up to 10 buttons.

Tile Pages

The room or home tile opens a page of buttons. Pressing a button raises its event and does whatever the installer connected to it.

Limitations/Known Issues

- The driver raises events only; it does not know the state of what the button controls.
- Up to 10 buttons.

Supported Features

- Up to 10 named buttons with icons
- Button events for Actions & Events
- Press actions for scenes and schedules
- Blank labels hide unused buttons

Test Environment

- Crestron Home OS 4.x

Supported Models

- FridayForge Button Tile

Contact Information

- Company: FridayForge
- Author: Aaron Johnson
- Email: aaron@forgedbyfriday.com

- Website: forGEDbyFriday.com

Version History

2.0.0 2026-10-30

Changes since Last Version

New Features

- Initial release

Licensing and Copyright Information

Certain Crestron products contain open source software. For specific information, please visit www.crestron.com/opensource

This driver is provided by FridayForge for use with Crestron Home. It is supplied as is, without warranty. Crestron, Crestron Home and related marks are trademarks of Crestron Electronics, Inc. Home Assistant, Pentair, IntelliCenter, Rachio, Bond, Ubiquiti, UniFi, Midea, MSmartHome, Levoit, VeSync, Jandy, AquaLink and iAquaLink are trademarks of their respective owners, which are not affiliated with FridayForge.